## GHM Messtechnik GmbH - Location Honsberg

Tenter Weg 2-8 • 42897 Remscheid • Germany Fon +49-2191-9672-0 • Fax -40

www.ghm-messtechnik.de • info@honsberg.com

## **Product Information**

# Flow Transmitter ABO-RT-I/U/F/C



- **High precision**
- No magnetic components in the flow space
- High pressure resistance
- 0..10 V, 4..20 mA, frequency/pulse output, completely configurable

#### Characteristics

A turbine acts as the primary sensor; its rotational speed is proportional to the flow rate. The rotational speed is detected by means of pre-tensioned Hall sensors, i.e. there are no magnets in the flow space.

The LABO-RT electronics make various output signals available:

- Analog signal 0/4..20 mA (LABO-RT-I)
- Analog signal 0/2..10 V (LABO-RT-U)
- Frequency signal (LABO-RT-F) or
- Value signal pulse / x litres (LABO-RT-C)

A model with switching output is also available (see separate datasheet).

If desired, the range end value can be set to the currently existing flow using "teaching".

#### Technical data

	,
Sensor	turbine with biased Hall sensor
Nominal width	DN 1550 (others on request)
Process	G <sup>1</sup> / <sub>2</sub> AG 2 A
connection	
Metering ranges	see table "Ranges"
Measurement	±1 % of full scale value
accuracy	in the specified metering range
	including linearity and
	repeatability
Max. particle size	0.5 mm
Pressure loss	0.3 bar at Q <sub>max</sub> .
Pressure	PN 250 bar
resistance	
Medium	-20+85 °C
temperature	optionally -20+150 °C (for 8 bar min.)
Ambient	-20+70 °C
temperature	
Storage	-20+80 °C
temperature	



## LABO-RT-I/U/F/C


Materials medium-contact     Housing stainless steel 315 stainless steel 430 Bearing tungsten carbide       Material Electronics housing     CW614N nickelled       Supply voltage     1030 V DC voltage output 10 V: 1530 V DC       Power consumption     < 1 W (without load)				
Bearing tungsten carbide				
Material Electronics housing  Supply voltage Voltage  Output data:  CW614N nickelled  1030 V DC voltage output 10 V: 1530 V DC  1 W (without load)  Curput data:  all outputs are resistant to short circuits ar reversal polarity protected  Current output: Voltage output: Voltage output: Voltage output: Frequency output: Frequency output: Pulse output:  I out = 100 mA max.  transistor output "push-pull" I out = 100 mA max.				
Electronics housing  Supply voltage  1030 V DC voltage output 10 V: 1530 V DC  Power consumption  Output data:  Current output: Voltage output: Voltage output: Voltage output: Frequency output: Pulse output:  Pulse output:  I out lout I out = 100 mA max.  I output data:  I output s are resistant to short circuits are reversal polarity protected 420 mA (020 mA available on request) output current max. 20 mA transistor output "push-pull" lout = 100 mA max.  transistor output "push-pull" lout = 100 mA max.				
Nousing   Supply voltage   1030 V DC voltage output 10 V: 1530 V DC				
Supply voltage				
voltage voltage output 10 V: 1530 V DC  Power consumption  Output data: all outputs are resistant to short circuits are reversal polarity protected  Current output: 420 mA (020 mA available on request)  Voltage 010 V (210 V available on request)  output: output current max. 20 mA  Frequency output: Iout = 100 mA max.  Pulse output: transistor output "push-pull"  Iout = 100 mA max.				
Power consumption  Output data:  Current output:  Voltage output:  Frequency output:  Pulse output:  Pulse output:  Voltage coutput:  Frequency output:  Pulse output:  Voltage coutput:  Frequency output:  Pulse output:  Voltage coutput:  Voltage				
consumption  Output data:  Current output:  Voltage output:  Frequency output:  Pulse output:  Output data:  all outputs are resistant to short circuits are reversal polarity protected  420 mA (020 mA available on request) O10 V (210 V available on request) output current max. 20 mA transistor output "push-pull" Iout = 100 mA max.  Indicate the short circuits are resistant to short circuits are reversal polarity protected  420 mA (020 mA available on request) output current max. 20 mA transistor output "push-pull" Iout = 100 mA max.				
Output data:  all outputs are resistant to short circuits are reversal polarity protected  420 mA (020 mA available on request)  Voltage output:  Frequency output:  Pulse output:  Iout = 100 mA max.  Institute of the control of				
reversal polarity protected  Current output:  Voltage output:  Frequency output:  Pulse output:  Iout = 100 mA max.  reversal polarity protected  420 mA (020 mA available on request) output current max. 20 mA transistor output "push-pull" Iout = 100 mA max.  Iout = 100 mA max.	اء ء			
Voltage output: 010 V (210 V available on request) output: current max. 20 mA  Frequency output: lout = 100 mA max.  Pulse output: transistor output "push-pull" lout = 100 mA max.	ıa			
output: output current max. 20 mA Frequency transistor output "push-pull" lout = 100 mA max.  Pulse output: transistor output "push-pull" lout = 100 mA max.				
Frequency output:   transistor output "push-pull"	010 V (210 V available on request)			
output: I <sub>out</sub> = 100 mA max. Pulse output: transistor output "push-pull" I <sub>out</sub> = 100 mA max.	output current max. 20 mA			
Pulse output: transistor output "push-pull"   I <sub>out</sub> = 100 mA max.				
I <sub>out</sub> = 100 mA max.				
1				
pulse width 50 ms pulse per volume is to be stated				
Display yellow LCD shows operating voltage				
(LABO-RT-I / U) or output status				
(LABO-RT-F / C)				
(rapid flashing = Programming)	,			
Electrical for round plug connector M12x1, 4-pole				
connection				
Ingress protection IP 67				
Weight see table in "Dimensions"				
<b>Conformity</b> CE	CE			


#### Signal output curves

Value x = Begin of the specified range


Current output







## Frequency output



f<sub>max</sub> selectable in the range of up to 2000 Hz

Other characters on request.

#### GHM Messtechnik GmbH - Location Honsberg

Tenter Weg 2-8 • 42897 Remscheid • Germany Fon +49-2191-9672-0 • Fax -40

www.ghm-messtechnik.de • info@honsberg.com




#### **Product Information**

#### Ranges

Types	Metering range (15 mm²/s)				
	l/min	m³/h			
RT-015AK001.	1.8 18	0.11 1.1			
RT-020AK002.	3.7 37	0.22 2.2			
RT-020AK004.	6.7 67	0.40 4.0			
RT-020AK008.	13.3 133	0.80 8.0			
RT-025AK016.	26.7 267	1.6016.0			
RT-040AK034.	56.7 567	3.4034.0			
RT-050AK068.	113.31133	6.8068.0			

## Wiring



Connection example: PNP NPN




Before the electrical installation, it must be ensured that the supply voltage corresponds to the data sheet.

It is recommended to use shielded wiring.

The push-pull output of the frequency or pulse output version can as desired be switched as a PNP or an NPN output.

## **Dimensions**



DN	G	ØD	SW / AF	Н	L	X	Range m³/h at 1-5 mm² /s	Weight kg
15	1/2	38	35	69	64	19	0.11 – 1.1	0.32
20	3/4	38	35	70	64	19	0.22 - 2.2	0.42
20	3/4	38	35	70	64	19	0.40 - 4.0	0.42
20	3/4	40	38	73	83	22	0.80 - 8.0	0.42
25	1	47	44	76	88	23	1.60 – 16.0	0.63
40	11/2	60	52	82	114	28	3.40 – 34.0	1.42
50	2	70	64	87	132	29	6.80 – 68.0	1.92

#### Handling and operation

#### Installation

As with all flow meters, if possible the turbine should be installed ahead of a valve (on the pressure side). Good degassing should be ensured. 10 x D calming sections are recommended before and after the turbine in order to maintain the specified accuracies. The turbine should be filled with fluid at all times.

The electronics housing does not project into the flow space.

#### Note

The fullscale end value can be programmed by the user via "teaching". Requirement for programmability must be stated when ordering, otherwise the device cannot be programmed.

The ECI-1 device configurator with associated software is available as a convenient option for programming all parameters by PC, and for adjustment.

The teaching option is not available for the pulse output version.

#### **Operation and programming**

The teaching process can be carried out by the user as follows:

- The flow rate to be set is applied to the device.
- Apply an impulse of at least 0.5 seconds and max. 2 seconds duration to pin 2 (e.g. via a bridge to the supply voltage or a pulse from the PLC), in order to accept the measured value.
- When the teaching is complete, pin 2 should be connected to 0 V, so as to prevent unintended programming.

The devices have a yellow LED which flashes during the programming pulse. During operation, the LED serves as an indicator of operating voltage (for analog output) or of switching status (for frequency or pulse output).

To avoid the need to transit to an undesired operating status for the purpose of teaching, the device can be provided ex-works with a teach-offset. The teach-offset point is added to the currently measured value before saving. The offset point can be positive or negative.

Example: The end of the metering range should be set to 80 %. However, only 60 % can be achieved without problem. In this case, the device would be ordered with a "teach-offset" of +20°%. At a flow rate of 60 % in the process, teaching would then store a value of 80 %.

If necessary, a far greater number of parameters can also be programmed using the ECI-1 device configurator.

#### GHM Messtechnik GmbH - Location Honsberg

Tenter Weg 2-8 ◆ 42897 Remscheid ◆ Germany Fon +49-2191-9672-0 ◆ Fax -40 www.ghm-messtechnik.de ◆ info@honsberg.com

## GHM-HONSBERG LABO-RT-I/U/F/C

## **Product Information**

### Ordering code

The base device RT-XXX is ordered with electronics e.g. LABO-RT-xxxx  $\,$ 



LABO - RT- 6. 7. 8. 9.

#### O=Option

1.	Nominal width						
	015 DN 15 - G <sup>1</sup> / <sub>2</sub> A						
	020	020 DN 20 - G <sup>3</sup> / <sub>4</sub> A					
	025	DN 25 - G 1 A					
	040	DN 40 - G 1 <sup>1</sup> / <sub>2</sub> A					
	050	DN 50 - G 2 A					
2.	Mechanic	al connection					
	Α	male thread					
3.	Housing r	material					
	K	stainless steel					
4.	Metering	range					
	001	0.11 1.1 m³/h					•
	002	0.22 2.2 m³/h				•	
	004	0.40 4.0 m³/h				•	
	008	0.80 8.0 m³/h				•	
	016	1.6016.0 m³/h			•		
	034	3.4034.0 m³/h		•			
	068	6.8068.0 m³/h	•				
5.	Connection for						
	E	electronics					

6.	Signal output				
	1	current output 420 mA			
	U	voltage output 010 V			
	F	frequency output (see "Ordering information")			
	С	pulse output (see "Ordering information")			
7.	Programn	Programming			
	N	cannot be programmed (no teaching)			
	Р О	programmable (teaching possible)			
8.	Electrical connection				
	S	for round plug connector M12x1, 4-pole			
9.	Optional				
	н о	100 °C version (with 300 mm cable)			

#### Required ordering information

For LABO-RT-F:
Output frequency at full scale
Maximum value: 2.000 Hz

#### For LABO-RT-C:

For the pulse output version, the volume (with numerical value and unit) which will correspond to one pulse must be stated.

Volume per pulse (numerical value)

Volume per pulse (unit)

Options for LABO

Special range for analog output:

## <= metering range (standard=metering range)

Special range for frequency output: <= metering range (standard=metering

**Power-On delay period** (0..99 s) (time after applying power during which the outputs are not actuated or set to defined

Further options available on request.

#### **Options**

range)

values)

- Flanged model,
- max. temperature 150 °C
- DN 80-300 PN 16
- model for air / gas
- range from 0.05 m³/h

## Accessories

- Cable/round plug connector (KB...) see additional information "Accessories"
- converter / counter OMNI-TA
- Device configurator ECI-1

l/min

s