GHM Messtechnik GmbH – Location Honsberg Tenter Weg 2-8 • 42897 Remscheid • Germany Fon +49-2191-9672-0 • Fax -40 www.ghm-messtechnik.de • info@honsberg.com

Product Information

Capacitive level transmitter / -switch incl. temperature control LCC2



- Developed for oil containers with highly disturbed level of fill
- No moving parts
- Automatic recognition of different types of oil via reference capacitance
- Temperature control can be integrated
- Switching output (push-pull) and analog output (4..20 mA or 0..10 V)
- Parameters can be programmed in order to achieve best possible adaptation to the application
- Simple adjustment
- Thread or flange fastening
- Compact size

Characteristics

The capacitive LCC2 oil measurer and switch monitors the level of the oil, even in containers with heavily mobile oil surfaces (compressors, engine oil sumps, gearboxes...).

The LCC2 measures the level in relationship to a reference structure at the end of the probe. As a result, levels are correctly detected with oil changes (different viscosity, at different temperatures or in the case of ageing of the oil) without recalibration.

An influence of the measurement from the container wall is to be disregarded by means of earthing (shielding on plug).

The programmable filter calculates the running average, and thus reduces the variations in the output signal without negatively affecting the accuracy.

The hysteresis of the switching point can also be adjusted by setting parameters.

The electronics belong to the class of intelligent sensors from HONSBERG, and thus enable the use of the ECI-1 interface (con-figurator). The USB-compatible interface enables the adjustment of numerous parameters for adaptation to the application.

The devices are delivered pre-configured according to customer wishes.

GHM-HONSBERG

Sensors and Instrumentation

Technical data

Sensor	Capacitive					
Mechanical Connection	G1 thread with two fastening nuts (screw flange as accessory)					
Metering range	200, 400, 600 mm (others on request)					
Measurement uncertainty	±1 % full scale value					
Reproducibility	±1 mm					
Pressure	PN 5 bar (with sealed sensor)					
resistance	,,					
Long term stability	±1 mm after 100,000 cycles (0100 % of level)					
Temperature dependency	±0.005 mm/ 1 K					
Medium temperature	-20+85 °C (optionally 100°C)					
Ambient temperature	-20+ 60 °C					
Supply voltage	1830 V DC (regulated)					
Current require- ment at rest	15 mA					
Analog	010 V or					
Output	420 mA					
Switching output	Push-Pull, 100 mA max. resistant to short circuits, reversed polarity protected					
LED (view from 4 sides)	yellow On = oil is within range Flashing =10 % above min. level Off = oil is below min. level or > tempera- ture limit (max. 95 °C) or defective. Flickering = with switchpoint programming with magnet. 2 x flashing confirms successful programming					
Ingress protection	on IP 67					
Materials	Housing	CW614N nickelled				
medium-contact	O-ring	FKM (EPDM optional)				
	Sensor	(NBR) FR4 (epoxy resin + fibre- glass), gold-plated Cu				
	Casting	Bectron PK 4342				
Materials non-medium-con- tact	Housing O-ring Plug	CW614N nickelled NBR PA6.6				
Weight	Sensor: 200 mm long 0.2 kg without flange Tube length: + 0.05 kg / 200 mm Flange: + 0.15 kg					
Conformity	CE REHS					

... professional Instruments "MADE IN GERMANY"

GHM Messtechnik GmbH – Location Honsberg Tenter Weg 2-8 • 42897 Remscheid • Germany Fon +49-2191-9672-0 • Fax -40 www.ghm-messtechnik.de • info@honsberg.com

Product Information

Wiring



Connection example: PNP NPN



Before the electrical installation, it must be ensured that the supply voltage corresponds to the data sheet.

It is recommended to use shielded wiring.

The push-pull output of the frequency or pulse output version can as desired be switched as a PNP or an NPN output.

Dimensions



GHM-HONSBERG

Sensors and Instrumentation

L= installation length (see ordering code), Lm = metering range (L-LT-LR) Standard 0 - 100%

Lt = Dead zone 10 mm

Lr = Reference zone 26 mm

(always in the same medium as the measuring zone) min = 10

LCC2 with flange



Standard flange dimensions



professional Instruments "MADE IN GERMANY"

Product Information

Installation

The threaded version can be either directly screwed into (G1") a hole (34 mm) or fastened using two supplied nuts.

Alternatively, a screw-on flange can be fastened on the thread, which is also made specifically for the customer. In order to achieve a tight seal the flange must be made with a suitable thread seal on the LCC2 unit. The container must have a suitable sealing surface on which the O-ring seals the flange. The flange must be free of contamination and mechanical damage. Bolts should be tightened only enough for the flange to abut against the housing wall.

A magnet clip is used for programming the switching point - if this is desired - \underline{or} for programming an offset to the start or full scales. Equally, the analog full scale may alternatively be programmed with the clip.

The clip can be inserted onto the plug connection or can be removed as a key.

The location to which to apply the clip for one second is marked on the label.



If the programmable switching point is desired:

- Set the level to the switching value or to the value from which the offset was desired.
- Hold the magnet against the marking.
- LED flickers
- Remove the magnet from the marking. Two LED pulses acknowledge successful programming.

With a minimum-switch, falling below the limit value causes a switchover to the alarm state. Return to the normal state occurs when the limit value plus the set hysteresis is once more exceeded.



Max Max-Hyst

With a maximum-switch, exceeding the limit value causes a switchover to the alarm state. Return to the normal state occurs when the measured value once more falls below the limit value minus the set hysteresis.

A changeover delay time (t_{DS}) can be applied to switching to the alarm state. One switch-back delay time (t_{DR}) of several can likewise be applied to switching back to the normal state.



In the normal state the integrated LED is on, in the alarm state it is off, and this corresponds to its status when there is no supply voltage.

In the non-inverted (standard) model, while in the normal state the switching output is at the level of the supply voltage; in the alarm state it is at 0 V, so that a wire break would also display as an alarm state at the signal receiver. Optionally, an inverted switching output can also be provided, i.e. in the normal state the output is at 0 V, and in the alarm state it is at the level of the supply voltage.



... professional Instruments "MADE IN GERMANY"

GHM-HONSBERG

Sensors and Instrumentation

GHM Messtechnik GmbH – Location Honsberg Tenter Weg 2-8 • 42897 Remscheid • Germany Fon +49-2191-9672-0 • Fax -40 www.ghm-messtechnik.de • info@honsberg.com

Product Information

A PowerOn delay function (ordered as a separate option) makes it possible to maintain the switching output in the normal state for a defined period after application of the supply voltage.

O=Option

1.	Form						
	в	Straight form (installation from					
	В	above) with protective tube					
2.	Connection						
	Н	Screw-in thread					
3.	Installation	stallation length L					
	200	200 mm (Lm= 164 mm)					
	400	400 mm (Lm= 364 mm)					
	600	600 mm (Lm= 564 mm)					
4.	Output signal						
	1	Current output 420 mA					
	U	Voltage output 010 V					
5.	Switching function						
	L	Minimum switch					
	Н	Maximum switch					
6.	Programming						
	N	Cannot be programmed (no teaching)					
	P O	Programmable (teaching possible)					
7.	Switching output level						
	0	Standard					
	1	Inverted					
8.	Electrical connection						
	S	For round plug connector M12x1, 4-pole					

GHM-HONSBERG

Sensors and Instrumentation

Accessories

flange



incl. O-ring (cannot be lost). For the dimensions, refer to Dimensions.

1. 2. 3. 4. FL-LCC2 - 75 M 4 - 60					
1.	. Outside diameter				
	75	Ø 75 mm			
2.	Connection material				
	Μ	CW614N nickelled			
3.	Perforation				
	4	Quadruple perforation			
4.	Pitch diameter				
	60	Ø 60 mm			

- Customer-specific flange on request
- Round plug connector / cable (KB...)
- Device configurator ECI-1

Options

Filter time	Off	0.2	0.5	1	2	4	8	16	32	sec
Special range for analogue output:										mm
<= Metering range (Standa range)	rd=N	Nete	ering	9						
Switching delay								,		s
(from Normal to Alarm)										
Switchback delay								,		s
(from Alarm to Normal)										
Power-on delay										s
(After connecting the supply which the switching output	y, tin is no	ne o ot a	durir ctiva	ng ateo	d)					
Switching output fixed (<	Lm))								mm
Special hysteresis (standa	ard=	5m	m)							mm
Temperature monitoring r	nax.	. 10	0 °C	;						°C

(Standard = 90 °C)

If the field is not completed, the standard setting is selected automatically.